

BELL SYSTEM PRACTICES Teletypewriter and Data Stations

SECTION P34.651 Issue 5, June, 1962 AT&TCo Standard

28 SINGLE-MAGNET TYPING REPERFORATOR REQUIREMENTS AND ADJUSTMENTS

CONTENTS	GRAPH
1. GENERAL	1.01-1.06
2. REQUIREMENTS AND ADJUSTMENTS	2.01-2.91
A. Single-magnet Typing Reperforator Function Mechanism	2.02-2.51
Function Clutch	
Drum Endplay (For One-shaft Unit)	2.02(B)
Drum Endplay (For Two-shaft Unit)	2.02(C)
Latchlever Spring	2.28(B)
Release Spring	2.26(A)
Shoe Lever	2.02(A)
Shoe Lever Spring	2.03(A)
Shoe Spring	2.03(B)
Triplever	2.11(B)
Follower Lever	2.12(A)
Release Lever Downstop Bracket	2.26(B)
Reset Arm	
Rocker Bail Guide Bracket	
Rocker Bail Lower Roller	
Punch Mechanism	
Detent Lever	2.20
Detent Lever Spring	2.24(B)
Feed-hole Lateral Alignment	
Feed-hole Spacing (Prel)	V
Feed-hole Spacing (Final)	the second second

28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 1

CONTENTS (Cont'd)	PARAGRAPH
Feed Pawl	2.18(B)
Feed Pawl Spring	2.24(A)
Main Triplever Spring	2.12(C)
Punch Drivelink Spring	2.14(C)
Punch Mounting Position (Prel)	2.14(A)
Punch Mounting Position (Final)	2.16
Punch Pin Penetration	2.15(A)
Punch Slide Downstop Position	2.15(B)
Punch Slide Guide	2.15(C)
Punch Slide Latch Springs	2.12(D)
Punch Slide Reset Bail	2.18(A)
Punch Slide Spring	2.22(A)
Reset Bail Triplever	2.17
Retractor Bail Springs	2.22(B)
Rocker Arm	2.14(B)
Tape Biasing Spring (Punch Block)	
Tape Biasing Spring (Tape Guide)	
Tape Shoe Torsion Spring	2.25(A)
Selector Mechanism	
Adjusting Arm Spring	2.12(B)
Marking Locklever Spring	2.06(B)
Pushlever Reset Bail Spring	2.08(A)
Range-finder Knob Phasing	2.09(A)
Selector Armature	2.04
Selector Armature Spring	2.06(A)
Selector Cam Lubricator	2.11(A)
Selector Clutch	ANAMARIA MANGARANGA
Drum	2.07(A)
Latchlever Spring	2.08(B)
Shoe Lever	2.02(A)
Shoe Lever Spring	2.03(A)
Shoe Spring	2.03(B)
Stoparm	2.09(B)
Selector Lever Spring	2.07(C)
Selector Magnet Bracket	2.05
Selector Pushlever Spring	2.07(B)

19

	2.08(C) 2.10
Typing Mechanism	
Accelerator Spring	2.44(B)
Axial Output Rack Guide Roller	2.39(A)
Axial Sector Alignment	2.38(A)
Bellcrank Springs	2.27(C)
Correcting Drivelink	2.40(A)
Correcting Drivelink Spring	2.36(D)
Eccentric Shaft Detent Lever Springs	2.38(B)
Function Blade Springs	2.36(B)
Function Box	2.29
Idler Gear Eccentric Shaft	2.40(B)
Lifter Arm	2.33(A)
Lifter Arm Eccentric Screw	2.33(B)
Lifter Spring	2.36(C)
Lifter Toggle Link Spring	2.36(A)
Locklever	2.34
Locklever Trip Post	2.35
LTRS-FIGS Assembly	
FIGS Arm Assembly Spring	2.31(B)
FIGS Extension Arm Spring	2.31(C)
LTRS Arm Assembly Spring	2.32(B)
LTRS Extension Arm Spring	2.32(C)
LTRS-FIGS Yield Arms (In FIGS	
Position)	2.32(A)
LTRS-FIGS Yield Arms (In LTRS	104 10E
Position)	2.31(A)
No. 5 Pulse Beam Spring	2.25(B)
Oscillating Drivelink	2.37(A)
Oscillating Drive Bail	2.37(B)
Pushbar Guide Bracket	2.39(B)
Pushbar Operating Blade (Prel)	2.27(A)
Pushbar Operating Blade (Final)	2.27(B)
Printing Latch Spring	2.44(D)
Printing Trip Link	2.44(A)
Printing Trip Link Spring	2.44(E)
Print Hammer	

28 SINGLE-MAGNET

P34.651

TYPING REPER-

CONTENTS (Cont'd) PA	RAGRAPH
Print Hammer Spring Print Hammer Torsion	2.44(C)
Spring (Resilient Hammer)	2.46
Ribbon-feed	2.43
Detent Spring (Helical-type Spring)	2.51
Drive Arm (Helical-type Spring)	2.50
Drive Arm Spring (Helical-type Spring)	2.51
Drive Arm Spring (Spring Washer)	2.48(A)
Eccentric Stud (Spring Washer)	2.47(B)
Pawl Downstop Eccentric (Spring Washe	r) 2.48(B)
Pawl Spring (Helical-type Spring)	2.50
Pawl Spring (Spring Washer)	2.47(A)
Reversing Arm Spring (Spring Washer)	2.49(B)
Ribbon Ratchet Wheel Spring Washers	2.48(C)
Ribbon Ratchet Wheel Torque Spring	2.50
Ribbon Reversing Plate (Spring Washer)	2.49(A)
Rocker Bail Pilot Stud	2.28(A)
Rotary Correcting Lever	. 2.41.2.42
Transfer Mounting Bracket	. 2.30
Typewheel	2.45(A)
B. Variable Features	
Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms	
Adjusting Lever (Common)	. 2.74(B)
Armature Backstop (Remote Control)	. 2.68
Armature Hinge (Remote Control)	. 2.67
Blocking Bail Spring (Remote Control)	. 2.68
Blocking Latch Torsion Spring (Remote	
Control)	. 2.68
Drive Arm Spring (Common)	. 2.73(A)
Drive Arm Adjusting Plate (Common)	. 2.73(B)
Drive Bail Spring (Remote Control)	. 2.67
Feed Pawl Spring (Common)	. 2.70(C)
Follower Lever (Common)	. 2.74(A)
Front Check Pawl Spring (Common)	. 2.70(C)
Latchlever (Automatic)	. 2.66(A)

Latchlever (Remote Control)	2.69
Latchlever Spring (Automatic)	2.66(D)
Latchlever Spring (Remote Control)	2.69
Magnet Assembly (Remote Control)	2.67
Mounting Plate (Remote Control)	2.67
Nonrepeat Lever Spring (Remote Control)	2.68
Ratchet Return Spring (Common)	2.71(C)
Ratchet Stop Block (Common)	2.70(B)
Rear Check Pawl (Common)	2.70(A)
Rear Check Pawl Spring (Common)	2.70(D)
Release Arm (Common)	2.72(A)
Release Arm Spring (Common)	2.72(B)
Release Lever (Remote Control)	2.68
Release Lever Spring (Automatic)	2.66(C)
Release Lever Spring (Remote Control)	2.69
Reset Bail Latch (Common)	2.77(A)
Reset Bail Latch Spring (Common)	2.77(B)
Reset Bail Triplever (Common)	2.75
Reset Bail Triplever Spring (Common)	2.77(C)
Safety Latch (Automatic)	2.66(B)
Safety Latch Spring (Automatic)	2.66(E)
Tape Length Adjusting Plate (Common)	2.76
Time Delay Lever (Common)	2.71(A)
Time Delay Lever Spring (Common)	2.71(B)
Auxiliary Timing Contact Mechanisms (Single-contact and Double-contact Types)	
Contact Alignment	2.84(B)
Contact Backstop (Double-contact Assembly).	2.84(A)
Contact Bracket (Prel) (For Units Equipped	` '
With One-cycle Cams)	2.86(B)
Left Contact Gap	2.85(C)
Left Contact Spring (Prel)	2.85(D)
Operating Bail Springs	2.86(A)
Right Contact Gap	2.85(A)
Swinger Contact Spring (Prel)	2.85(B)

28 SINGLE-MAGNET

CONTENTS (Cont'd) PAI	PARAGRAPH	
Backspace Mechanisms (Manual and Power Drive)	118 9)	
Armature Bail Spring (Power Drive)	. 2.65(D)	
Armature Hinge (Power Drive)	. 2.60(A)	
Armature Upstop (Power Drive)	. 2.60(B)	
Bellcrank Spring (Common)	. 2.65(C)	
Drivelink (Power Drive) (Prel)	. 2.61(A)	
Drivelink (Power Drive) (Final)	. 2.61(B)	
Feed Pawl (Common) (Prel)	. 2.59(B)	
Feed Pawl (Common) (Final)	. 2.61(B)	
Feed Pawl Adjusting Plate (Common)	. 2.58(B)	
Feed Pawl Spring (Common)	. 2.65(B)	
Gear Segment Spring (Common)	. 2.65(E)	
Latch (Power Drive)	2.63	
Latch Extension (Power Drive)	2.62	
Latch Extension Spring (Power Drive)	. 2.65(F)	
Latch Spring (Common)		
Nonrepeat Arm (Power Drive)	2.65(A) 2.64	
Rake (For Chadless Tape Units Only)	2.04	
(Common)	2.58(A)	
Return Latch (Common)	2.59(A)	
Code-reading Contact Mechanisms (Make-only and Transfer Types)		
Contact Bracket (Make-only Contacts) (Prel)	2.83	
Contact Bracket (Transfer Contacts) (Prel)	2.82	
Contact Mounting Bracket (Common)	2.81(A)	
Contact Mounting Plate (Common)	2.81(B)	
Marking Contact Backstops (Common)	2.79(A)	
Marking Contact Springs (Common) (Prel) .	2.79(B)	
Spacing Contact Backstops (Transfer	2014011.0 3 -014- 2	
Contacts) (Prel)	2.80(B)	
Spacing Contact Springs (Transfer		
Contacts) (Prel)	2.80(C)	
Swinger Contact Springs (Common) (Prel)	2.80(A)	
Contact-timing Measurements	A Trail Assessment	
Auxiliary Timing Contacts	2.90	
Code-reading Contacts	2.90	
	2.07	

LTRS-FIGS Contacts	2.91
To Zero Test Set	2.88
External Manual Interfering LTRS Tape Feed-out Mechanism	
Arm	2.78(B)
Feed-out Lever	2.78(A)
LTRS-FIGS Contact Mechanism	
Lower Contact Spring	2.87(B)
Middle Contact Spring	2.87(A)
Mounting Bracket	2.87(D)
Operating Lever Spring	2.87(C)
Manual-and Solenoid-operated Interfering LTRS Tape Feed-out Mechanisms	
Drive Shaft Rear Bearing	2.56
Triplever (Manually Operated)	2.57(B)
Triplever (Solenoid Operated)	2.57(A)
Triplever Spring	2.57(C)
Signal-bell Contact Mechanisms	
Contact Bracket Assembly (Leaf-type Switch)	2.54(B)
Contact Mounting Bracket (Overcentering-	
type Switch)	2.53(A)
Function Blade Spring	2.53(B),
	2.54(C)
Signal Bell Contact (Leaf-type Switch)	2.54(A)
Tape Guide Mechanism	
Tape Guide	2.55
Unshift-on-Space Mechanism	
Function Blade	
Function Blade Spring	2.52(B)
SSOCIATED BELL SYSTEM PRACTICE	3.01

28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

Page 7

1. GENERAL

1.01 This section contains the specific requirements and adjustments for the 28 single-magnet typing reperforator. The material herein, together with the section containing the general requirements on teletypewriter apparatus, provides the complete adjusting information for maintenance.

1.02 This section is reissued to revise various adjustment requirements in accordance with changes authorized for this apparatus by P98 series Bell System Practices listed at the end of this section, to include other authorized revisions and additions so as to bring the section generally up to date, and to change the title. Since this is a general revision, the marginal arrows ordinarily used to indicate changes have been omitted.

1.03 References to left or right, front or rear, and up or down refer to the apparatus in its normal operating position as viewed from the front with the selector mechanism to the right and the punch mechanism to the left.

1.04 When a requirement calls for the clutch to be disengaged, the clutch-shoe lever must be fully latched between its triplever (or stoparm) and latchlever so that the clutch shoes release their tension on the clutch drum. When engaged, the clutch-shoe lever is unlatched and the clutch shoes are wedged firmly against the clutch drum.

Note: When the main shaft is rotated by hand, the clutches do not fully disengage upon reaching their stop positions. In order to relieve the drag on the clutches and permit the main shaft to rotate freely, use a screwdriver to apply pressure on the stop lug of each clutch disc to cause it to engage its latchlever and thus disengage the internal expansion clutch.

1.05 Manual Selection of Characters or Functions: To manually operate the single-magnet typing reperforator, proceed as follows:

(1) Attach the armature clip to the selector magnet armature by carefully putting the flat-formed end of the armature clip over the top of the armature between the pole pieces and then hooking the projection under the edge of the armature. Finally, hook the top end of the armature clip over the top of the bakelite guard of the selector coil terminal. The spring tension of the armature clip will hold the selector armature in the marking (attracted) position.

(2) While holding the selector magnet armature operated by means of the armature clip, use the handwheel included with the special tools for servicing 28 teletypewriter apparatus to manually rotate the main shaft in a counterclockwise direction until all the clutches are brought to their disengaged position.

- (3) Fully disengage all clutches in accordance with 1.04,
- (4) Release the selector magnet armature momentarily to permit the selector clutch to engage.
- (5) Rotate the main shaft slowly until all the pushlevers have fallen to the left of their selecting levers.
- (6) Strip the pushlevers from their selector levers, which are spacing in the code combination of the character function that is being selected, and allow the pushlevers to move to the right.
- (7) The pushlevers and the selector levers move in succession starting with the inner lever No. 1 to the outer lever No. 5.
- (8) Continue to rotate the main shaft until all operations initiated by the selector action clear through the unit.
- Where a single-magnet typing reperforator is used as 1.06 a component of the 28 reperforator-transmitter unit or the 28 perforator-transmitter-base, refer to the applicable requirement sections for the additional adjustment requirements.

2. REQUIREMENTS AND ADJUSTMENTS

The following figures show the adjusting tolerances, position of parts, and spring tensions. The illustrations are arranged so that the adjustments are in the sequence that would be followed if a complete readjustment of apparatus were being made. In some cases, where an illustration shows interrelated parts, the sequence that should be followed in checking the requirements and making the adjustments is indicated by the letters (A), (B), (C), etc.

28 SINGLE-MAGNET

P34.651

Page 9


TYPING REPER-

A. Single-magnet Typing Reperforator

2.02 Selector and Function Mechanisms


Note: To facilitate adjustments, remove typing reperforator from base as follows:


- For typing reperforator equipped with one-shaft mechanism, refer to section containing the disassembly and reassembly routines for the 28 typing reperforator.
- For typing reperforator equipped with two-shaft mechanism, refer to section containing the disassembly and reassembly routines for the 28 perforator-transmitter-base.



2.03 Selector and Function Mechanisms

NOTE: THESE SPRING TENSIONS APPLY TO BOTH CLUTCHES.





28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 11

2.04 Selector Mechanism

NOTE


TO FACILITATE MAKING THE FOLLOWING ADJUSTMENTS, REMOVE THE RANGE FINDER AND SELECTOR MAGNET ASSEMBLIES. TO INSURE BETTER OPERATION, PULL A PIECE OF KS BOND PAPER BETWEEN THE ARMATURE AND THE POLE PIECES TO REMOVE ANY OIL OR FOREIGN MATTER THAT MAY BE PRESENT. MAKE CERTAIN THAT NO LINT OR PIECES OF PAPER REMAIN BETWEEN THE POLE PIECES AND ARMATURE.



TO ADJUST

- 1. POSITION ARMATURE SPRING ADJUSTING NUT TO HOLD ARMATURE FIRMLY AGAINST PIVOT EDGE OF CASTING.
- 2. POSITION ARMATURE AND BACKSTOP WITH MOUNTING SCREWS LOOSENED.

2.05 Selector Mechanism



SPACING LOCK LEVER ON HIGH PART OF CAM. ARMATURE IN CONTACT WITH POLE PIECE. SOME CLEARANCE BETWEEN UPPER SURFACE OF ARMATURE EXTENSION AND LOWER SURFACE OF SPACING LOCK LEVER WHEN LOCK LEVER IS HELD DOWNWARD

MAX. 0.003 INCH

TO ADJUST

POSITION UPPER END OF MAGNET BRACKET. TIGHTEN TWO MAGNET BRACKET MOUNTING SCREWS. RECHECK REQUIREMENT (1).


28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 13

2.06 Selector Mechanism



2.07 Selector Mechanism



TO ADJUST

LOOSEN THE CLUTCH DRUM MOUNTING SCREW AND POSITION THE CLUTCH DRUM SECURELY AGAINST THE SHOULDER OF THE MAIN SHAFT AND TIGHTEN THE MOUNTING SCREW.


28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 15

2.08 Selector Mechanism



2.09 Selector Mechanism

NOTE: REPLACE RANGE FINDER AND SELECTOR MAGNET ASSEMBLY.


(A) RANGE FINDER KNOB PHASING

REQUIREMENT

WITH RANGE FINDER KNOB TURNED TO EITHER END OF RACK, ZERO MARK ON SCALE SHALL BE WITHIN 3 POINTS OF SCRIBED LINE ON RANGE FINDER PLATE.

TO ADJUST

REMOVE MOUNTING NUT, DISENGAGE KNOB FROM RACK, AND POSITION KNOB. RE-ENGAGE KNOB WITH RACK AND REPLACE MOUNTING NUT.



RANGE SCALE SET AT 60. SELECTOR CLUTCH DISENGAGED. ARMATURE IN MARKING POSITION. CLUTCH STOP ARM SHALL:ENGAGE CLUTCH SHOE LEVER BY APPROXIMATELY FULL THICKNESS OF SHOE LEVER. TO ADJUST

POSITION STOP ARM ON STOP ARM BAIL WITH CLAMP SCREW LOOSENED.


28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 17

2.10 Selector Mechanism



2.11 Selector and Function Mechanisms



DIT OF THE TRANSPORT WHEN THE PARTY TO SEE THE PERSON OF T

28 SINGLE-MAGNET TYPING


P34.651

Page 19


TYPING REPER-FORATOR

2.12 Selector, Function, and Punch Mechanisms

Note: For typing reperforator equipped with remote-control or automatic noninterfering LTRS tape feed-out mechanism, substitute the follower lever adjustment shown in 2.74(A).



2.13 Function Mechanism



28 SINGLE-MAGNET


P34.651

TYPING REPER-

Page 21


2.14 Punch Mechanism

Note: For typing reperforator equipped with two-shaft mechanism, refer to the section containing the requirements and adjustments for the 28 perforator-transmitter-base.




*AFTER FEED PAWL ADJUSTMENT HAS BEEN MADE, IF PUNCH PIN PENETRATION AND FEED PAWL REQUIREMENTS ARE MET, THIS REQUIREMENT SHALL BE CONSIDERED FULFILLED.

Punch Mechanism 2.15



SHAFT.



(LEFT SIDE VIEW) (C) PUNCH SLIDE GUIDE

REQUIREMENT

LTRS SELECTED. FUNCTION CLUTCH ENGAG-ED AND ROTATED UNTIL THE PUNCH SLIDES JUST TOUCH THE PUNCH PINS. THE PUNCH SLIDES SHALL ALIGN CENTRALLY WITH THEIR RESPECTIVE PUNCH PINS (GAUGED BY EYE).

TO ADJUST POSITION THE PUNCH SLIDE GUIDE WITH ITS MOUNTING NUTS LOOSENED.

28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 23

2.16 Punch Mechanism

Note: Where a typing reperforator is part of a 28 perforator-transmitter-base, omit Part (1) of this adjustment.

PUNCH MOUNTING POSITION --- FINAL
(1) TO CHECK (SEE NOTE ABOVE)
SELECT LTRS CODE COMBINATION (12345). ROTATE MAIN SHAFT UNTIL FUNCTION CLUTCH TRIPS. REQUIREMENT CLEARANCE BETWEEN PUNCH SLIDE AND PUNCH SLIDE LATCH MIN. 0.020 INCH----MAX. 0.030 INCH-AT SLIDE WHERE CLEARANCE IS LEAST. TO ADJUST LOOSEN REPERFORATOR MOUNTING SCREWS, ADJUSTING CLAMP LOCK SCREW, ADJUSTING CLAMP PIVOT SCREW. AND ANCHOR BRACKET SCREW UNTIL FRICTION TIGHT. PLACE TIP OF SCREWDRIVER BETWEEN SCREW AND RIM OF PRY HOLE AND PRY REPERFORATOR UP OR DOWN. TIGHTEN ONLY ADJUSTING CLAMP LOCK SCREW. (2) TO CHECK WITH UNIT IN LTRS POSITION, CLEARANCE SHALL BE BETWEEN TAPE GUIDE AND CHARACTER"M". SELECT "V" CODE COMBINATION (+2345). TRIP FUNCTION CLUTCH AND MOVE ROCKER BAIL TO EXTREME LEFT. REQUIREMENT CLEARANCE BETWEEN TAPE GUIDE AND TYPEWHEEL CHARACTER "M" MIN. 0.075 INCH----MAX. 0.095 INCH TO ADJUST REMOVE RIBBON FROM CARRIER, POSITION REPERFORATOR WITH TWO MOUNTING SCREWS, ADJUSTING CLAMP PIVOT SCREW, AND ANCHOR BRACKET SCREW LOOSENED. CHECK RESET BAIL TRIP LEVER REQUIREMENT FOR SOME CLEARANCE AND ADJUST IF NECESSARY. REPERFORATOR TYPEWHEEL CHARACTER "M" TYPEWHEEL . ADJUSTING CLAMP LOCK SCREW TAPE GUIDE ADJUSTING CLAMP PIVOT SCREW \circ PUNCH SLIDE REPERFORATOR MOUNTING SCREW PUNCH SLIDE 0 LATCH PRY HOLE -ANCHOR BRACKET ANCHOR BRACKET SCREW-SCREW (ALTERNATE POSITION) REPERFORATOR MOUNTING SCREW-


2.17 Punch Mechanism

Note:

1. For typing reperforator equipped with two-shaft mechanism, omit

this adjustment.

 For typing reperforator equipped with remote-control or automatic noninterfering LTRS tape feed-out mechanism, substitute the reset bail triplever adjustment shown in 2.75.



28 SINGLE-MAGNET

P34.651

TYPING REPER-


2.18 Punch Mechanism

RESET BAIL

DETENT LEVER

LOCK SCREW

FEED PAWL ECCENTRIC -



TO LEVER, DETENT ROLLER IN CONTACT WITH RATCHET WHEEL, HIGH PART OF FEED PAWL ECCENTRIC TO THE RIGHT OF ITS LOCK SCREW, FEED PAWL . THE FEED PAWL SHALL ENGAGE THE FIRST TOOTH BELOW A HORIZONTAL CENTERLINE

THROUGH RATCHET WHEEL WITH NO PERCEPTIBLE CLEARANCE.

TO ADJUST

ROTATE THE FEED PAWL ECCENTRIC WITH LOCK SCREW LOOSENED. NOTE THIS ADJUSTMENT IS RELATED TO FEED HOLE.
SPACING AND TWO ADJUSTMENTS

SHALL BE MADE AT THE SAME TIME.

2.19 Punch Mechanism

Note: To replace the typing reperforator on the base, proceed as follows:

For typing reperforator equipped with one-shaft mechanism, refer to section containing the disassembly and reassembly routines for the 28 typing reperforator.

For typing reperforator equipped with two-shaft mechanism, refer to section containing the disassembly and reassembly routines for the 28 perforator-trnsmitter-base.

FEED HOLE SPACING ---- PRELIMINARY.


REQUIREMENT

INDENT OF DIE WHEEL ECCENTRIC STUD POINTING DOWNWARD,

TO ADJUST POSITION DIE WHEEL ECCENTRIC STUD WITH LOCK NUT LOOSENED.

BEFORE PROCEEDING WITH THE FOLLOWING ADJUSTMENTS, CHECK BOTH BIASING SPRING ADJUSTMENTS. FEED HOLE SPACING -

(1) REQUIREMENT WITH TAPE SHOE BLOCKED AWAY FROM FEED WHEEL, FEED PAWL, AND
DETENT DISENGAGED, AND TAPE REMOVED: FEED WHEEL SHALL ROTATE FREELY.
(SHALL BE CHECKED THROUGH 3 OR 4 REVOLUTIONS.)



PERFORATE IN ORDER SIX SEQUENCES MADE UP OF NINE BLANK CODE COMBINATIONS
FOLLOWED BY A LTRS COMBINATION. OPEN CHADS SO THAT CODE HOLES ARE
VISIBLE. PLACE TAPE OVER SMOOTH SIDE OF TPT 56011 TAPE GAUGE SO THAT FIRST NO. 2
CODE HOLE IS CONCENTRIC WITH FIRST (0.072 INCH) HOLE IN GAUGE. (SEE NOTE BELOW.) REQUIREMENT

SECOND THROUGH FIFTH HOLE IN GAUGE VISIBLE THROUGH NO. 2
HOLES IN TAPE. CIRCULAR PORTION OF SIXTH NO. 2 CODE HOLE ENTIRELY WITHIN
CORRESPONDING (0.086 INCH) HOLE IN GAUGE.

TO ADJUST

A- WITH TAPE REMOVED, KEEPING INDENT BELOW CENTER OF STUD, POSITION DIE WHEEL ECCENTRIC STUD WITH LOCK NUT LOOSENED SO THAT DIE WHEEL JUST BINDS ON FEED WHEEL. BACK OFF ECCENTRIC STUD SO THAT FEED WHEEL IS JUST FREE TO ROTATE. CHECK FREENESS THROUGH 3 OR 4 REVOLUTIONS OF WHEEL. MOVE INDENT IN

B. REFINE THE ABOVE ADJUSTMENT TO MEET REQUIREMENT UNDER (2). MOVE INDENT I ECCENTRIC STUD TOWARD FEED WHEEL TO DECREASE AND AWAY FROM FEED WHEEL TO INCREASE FEED HOLE SPACING. CAUTION: WITH TAPE REMOVED, MAKE SURE FEED WHEEL AND DIE WHEEL DO NOT BIND,

C. RECHECK REQUIREMENT (1). IF IT IS NOT MET, ECCENTRIC HAS BEEN OVER ADJUSTED. REFINE.

NOTE:

FIRST THROUGH FIFTH HOLES IN GAUGE ARE SAME SIZE AS CODE HOLES IN TAPE (0.072 INCH DIAMETER). BUT SIXTH HOLE IN GAUGE IS LARGER (0.086 INCH). THIS ARRANGE-MENT ALLOWS \$ 0.007 INCH VARIATION IN 5 INCHES.


28 SINGLE-MAGNET

TYPING P34.651 REPER-

Page 27

18.10

2.20 Punch Mechanism




DETENT LEVER

REQUIREMENT


A PIECE OF TAPE CONTAINING NINE FEED HOLES FOLLOWED BY 'LTRS COMBINATION PERFORATED ON REPERFORATOR MUST CONFORM TO THE TP 156011 TAPE GAUGE. THE LATERAL CENTERLINE THROUGH THE CODE HOLES IN THE TAPE SHALL COINCIDE WITH A LATERAL CENTERLINE THROUGH THE HOLES IN THE GAUGE.


TO ADJUST

ROTATE THE DETENT ECCENTRIC CLOCKWISE TO MOVE
THE FEED HOLES TOWARD THE HINGED EDGE OF THE
CODE HOLES AND COUNTERCLOCKWISE TO MOVE THE
FEED HOLES TOWARD THE TRAILING EDGE OF THE CODE
HOLES. TIGHTEN THE ECCENTRIC LOCK NUT AND REFINE THE FEED PAWL ADJUSTMENT.



2.21 Punch Mechanism






28 SINGLE-MAGNET

P34.651

TYPING REPER-


Page 29

2.22 Punch Mechanism




TO FACILITATE REHOOKING TENSION SPRINGS, PLACE PUNCH PINS IT! UPPERMOST POSITION.


2.23 Punch Mechanism




28 SINGLE-MAGNET TYPING P34.651 REPER-FORATOR


2.24 Punch Mechanism





2.25 Punch and Typing Mechanisms






28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 33

2.26 Function Mechanism



2.27 Typing Mechanism



28 SINGLE-MAGNET


P34.651

TYPING REPER-

Page 35

35 Law 17 1 1 1


2.28 Function and Typing Mechanisms




MIN. 0.005 INCH MAX. 0.020 INCH AT THE POINT IN THE CYCLE WHERE THIS CLEARANCE IS AT A MINIMUM.


TO ADJUST

POSITION ROCKER BAIL PILOT STUD IN ELONGATED HOLE WITH LOCK NUT LOOSENED.



2.29 Typing Mechanism





FUNCTION BOX

TO CHECK

MANUALLY SELECT LTRS CODE COMBINATION (12345).

ROTATE MAIN SHAFT UNTIL FUNCTION CLUTCH TRIPS,

PUNCH SLIDES ARE DISENGAGED FROM LATCHES

AND BLADE JUST TOUCHES PUSH BARS. IN NO. 2 AND 3

PUSH BARS, TAKE UP PLAY DOWNWARD AND RELEASE.

REQUIREMENT

TOP SURFACE OF OPERATING BLADE

BELOW TOP SURFACE OF NO. 2 AND 3 PUSH BARS.

TO ADJUST

USING PRY POINT, POSITION FUNCTION BOX WITH THREE MOUNTING SCREWS IN REAR PLATE AND ONE MOUNTING SCREW IN FRONT PLATE LOOSENED. CHECK POSITION OF BELL CRANK SPRING BRACKET.

NOTE:

WHERE A TYPING REPERFORATOR IS PART OF A 28
PERFORATOR-TRANSMITTER-BASE, IT MAY BE NECESSARY
TO REFINE THE FUNCTION-BOX ADJUSTMENT WITHIN ITS
LIMITS TO INCREASE OPERATING MARGINS OF A TYPING
REPERFORATOR.


28 SINGLE-MAGNET

P34.651


TYPING

Page 37 FORATOR

2.30 Typing Mechanism




2.31 Typing Mechanism





28 SINGLE-MAGNET
TYPING
Page 39 FORATOR

2.32 Typing Mechanism



2.33 Typing Mechanism





28 SINGLE-MAGNET

UNIT IS SO EQUIPPED.


P34.651

TYPING REPER-

Page 41

FORATOR

2.34 Typing Mechanism




POSITION LOCK LEVER ON LOCK ARM ASSEMBLY WITH CLAMP SCREW FRICTION TIGHT.

NOTE:

TO AVOID INTERFERENCE WITH LOCK LEVER, IT MAY BE NECESSARY TO MOVE HIGH PART OF CORRECTING DRIVE LINK ECCENTRIC BUSHING ABOVE HORIZONTAL CENTER LINE.

2.35 Typing Mechanism




(REAR VIEW)

28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

2.36 Typing Mechanism



2.37 Typing Mechanism

(A) OSCILLATING DRIVE LINK

TO CHECK


POSITION ROCKER BAIL TO ITS EXTREME LEFT.

REQUIREMENT

SECTOR MOUNTING STUD, TOGGLE PIVOT SCREW, AND OSCILLATING DRIVE BAR.
MOUNTING SCREW SHALL APPROXIMATELY LINE UP.

TO ADJUST

POSITION OSCILLATING DRIVE LINK BY MEANS OF ITS ECCENTRIC BUSHING.



(B) OSCILLATING DRIVE BAIL

TO CHECK

MANUALLY SELECT BLANK CODE COMBINATION.
ROTATE MAIN SHAFT UNTIL ROCKER BAIL IS TO
EXTREME LEFT.

REQUIREMENT

(1) ROLLER ON AXIAL CORRECTING PLATE SEATED FIRMLY IN CENTER OF FIRST NOTCH OF AXIAL SECTOR.

TO ADJUST

WITH OSCILLATING DRIVE BAIL MOUNTING SCREW LOOSENED, POSITION THE CORRECTING DRIVE LINK SO THAT THE ROLLER FITS SNUGLY IN FIRST NOTCH. ROLLER SHALL RIDE CENTRALIZED IN NOTCH WITH NOTCH TOUCHING BOTH SIDES, AND THE DRIVE BAIL SHALL BE LOOSE AND IN POSITION CORRESPONDING TO THAT OF CORRECTING PLATE.

28 SINGLE-MAGNET


P34.651

TYPING REPER-


Page 45

FORATOR


2.38 Typing Mechanism



2.39 Typing Mechanism



(TOP VIEW)




28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

Page 47

2.40 Typing Mechanism



2.41 Typing Mechanism

ROTARY CORRECTING LEVER

(1) TO CHECK
LOOSEN CORRECTING CLAMP ADJUSTING SCREW. WITH UNIT IN FIGS CONDITION,
SELECT NO. 9 CODE COMBINATION (---45). TRIP FUNCTION CLUTCH AND POSITION
ROCKER BAIL TO EXTREME LEFT. MANUALLY SEAT ROTARY CORRECTING LEVER IN TYPE
WHEEL RACK.


REQUIREMENT

SECOND TOOTH FROM TOP OF RACK SEATED BETWEEN LOBES OF CORRECTING LEVER.

LOOSEN ECCENTRIC BUSHING LOCK NUT. WITH CLAMP ADJUSTING SCREW LOOSENED

AND CORRECTING LEVER PIVOT TO RIGHT OF CENTER LINE, POSITION CORRECTING
LEVER. TIGHTEN BUSHING LOCK NUT. DO NOT TIGHTEN CLAMP ADJUSTING SCREW
AT THIS TIME.

(2) TO CHECK
IN A MANNER SIMILAR TO THAT DESCRIBED ABOVE, CHECK ENGAGEMENT OF FIFTH
TOOTH (--34- CODE COMBINATION SELECTED IN FIGS CONDITION), NINTH TOOTH
(--4- CODE COMBINATION SELECTED IN LTRS CONDITION), AND SIXTEENTH TOOTH
(--3-5 CODE COMBINATION SELECTED IN LTRS CONDITION).




28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

Page 49

2.43 Typing Mechanism





28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

2.44 Typing Mechanism





28 SINGLE-MAGNET


P34.651

TYPING REPER-

Page 53

FORATOR

2.46 Typing Mechanism



PRINT HAMMER TORSION SPRING (RESILIENT HAMMER)
REQUIREMENT


WITH CLUTCHES LATCHED IN STOP POSITION AND PUSH END OF SCALE APPLIED TO PRINT HAMMER LEVER

MIN. 1/2 OZ. --- MAX. 2 OZS.

TO PUSH TOP OF PRINT HAMMER HEAD SO AS TO BE LEVEL WITH CHARACTERS ON BOTTOM OF TYPEWHEEL.

2.47 Typing Mechanism

Note: On units equipped with spring washer behind ribbon spool.



28 SINGLE-MAGNET

P34.651

TYPING


REPER-

Page 55

FORATOR


2.48 Typing Mechanism

Note: On units equipped with spring washer behind ribbon spool.



2.49 Typing Mechanism

Note: On units equipped with spring washer behind ribbon spool.



28 SINGLE-MAGNET
TYPING


P34.651

REPER-FORATOR

Page 57


2.50 Typing Mechanism

Note. On units equipped with helical-type spring behind ribbon spool.



2.51 Typing Mechanism

Note: On units equipped with helical-type spring behind ribbon spool.



TO PULL DETENT SPRING TO ITS

INSTALLED LENGTH.


28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

2.53 Signal-bell Contact Mechanisms

Note: On units equipped with overcentering-type switch.




28 SINGLE-MAGNET

P34.651


TYPING REPER-FORATOR

2.54 Signal-bell Contact Mechanisms

Note: On units equipped with leaf-type switch.



2.55 Tape-guide Mechanism




28 SINGLE-MAGNET

P34.651


TYPING REPER-FORATOR

Page 63

2.56 Manual- and Solenoid-operated Interfering LTRS Tape Feed-out Mechanisms



2.57 Manual- and Solenoid-operated Interfering LTRS Tape Feed-out Mechanisms



28 SINGLE-MAGNET


P34.651


TYPING REPER-

Page 65


FORATOR

2.58 Backspace Mechanisms (Manual and Power Drive)






Backspace Mechanisms (Manual and Power Drive) 2.59



REQUIREMENT

BACKSPACE MECHANISM IN UNOPERATED POSITION. CLEARANCE BETWEEN RETURN LATCH AND FEED PAWL EXTENSION: MIN. 0.004 INCH MAX. 0.020 INCH TO ADJUST

ADJUST ECCENTRIC WITH MOUNTING SCREW FRICTION TIGHT.



BACKSPACE BELL CRANK ASSEMBLY IN OPERATED POSITION (BELL CRANK DOWNWARD, IN LOWEST POSITION), AND FEED WHEEL DETENTED BACK ONE SPACE. CLEARANCE BETWEEN FEED WHEEL RATCHET TOOTH AND FEED PAWL MIN. SOME --- MAX. 0.003 INCH CHECK WITH FEED WHEEL SHAFT OIL HOLE IN UPPERMOST POSITION AND RECHECK EACH 90 DEGREES ABOUT THE PERIPHERY OF FEED WHEEL.

TO ADJUST
BY MEANS OF 0.060 INCH ALLEN WRENCH, ROTATE
ECCENTRIC WITH NUT POST FRICTION TIGHT.

28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

Page 67

2.60 Backspace Mechanism (Power Drive)

(A) ARMATURE HINGE
REQUIREMENT
ARMATURE BAIL SPRING REMOVED. WITH ARMATURE HELD
AGAINST POLE FACE AND PLAY TAKEN UP AT HINGE IN
DOWNWARD DIRECTION, CLEARANCE BETWEEN ARMATURE AND
MAGNET BRACKET

MIN. SOME

MAX. 0.004 INCH

TO ADJUST
WITH MOUNTING SCREWS LOOSENED, POSITION HINGE. WHILE
ADJUSTMENT IS BEING MADE, ARMATURE SHALL TOUCH
FRONT AND REAR OF POLE FACE.

ARMATURE


POLE FACE

MAGNET MOUNTING
BRACKET


MOUNTING SCREWS

HINGE

THIS ADJUSTMENT IS MADE AT FACTORY AND SHALL NOT BE DISTURBED UNLESS A REASSEMBLY OF THE UNIT IS UNDERTAKEN. IF NECESSARY TO MAKE THIS ADJUSTMENT, THE PUNCH UNIT SHALL BE REMOVED. SEE DISASSEMBLY AND REASSEMBLY. REMAKE THE PUNCH UNIT POSITION ADJUSTMENT.



Backspace Mechanisms (Manual and Power Drive) 2.61



(A) DRIVE LINK (POWER DRIVE ONLY - PRELIMINARY)

REQUIREMENT

BACKSPACE MECHANISM IN OPERATED POSITION, FEED WHEEL IN DETENTED POSITION. LATCH ENGAGED WITH ECCENTRIC ARM. HIGH PART OF ECCENTRIC TO RIGHT. CLEARANCE BETWEEN FEED PAWL AND FEED WHEEL RATCHET TOOTH

SOME MIN.

0.003 INCH MAX.

CHECK WITH FEED WHEEL SHAFT OIL HOLE IN UPPERMOST POSITION AND RECHECK EACH 90 DEGREES ABOUT THE PERIPHERY OF FEED WHEEL.

TO ADJUST

BY MEANS OF PRY POINT, POSITION ADJUSTING LINK WITH DRIVE LINK SCREW FRICTION TIGHT.

(B) FEED PAWL (MANUAL AND POWER DRIVE-FINAL) AND DRIVE LINK (POWER DRIVE ONLY - FINAL)

TO CHECK

PLACE FEED WHEEL SHAFT OIL HOLE IN UPPERMOST POSITION.
OPERATE BACKSPACE MECHANISM ONCE.
REQUIREMENT UNIT OPERATING UNDER POWER AND TAPE IN PUNCH UNIT.

RATCHET WHEEL SHALL BE BACKED ONE SPACE TO A FULLY DETENTED POSITION. CHECK FOR EACH 90 DEGREES ABOUT THE PERIPHERY OF FEED WHEEL.

NOTE: A FULLY DETENTED POSITION IS DEFINED AS: "WITH DETENT ROLLER IN CONTACT WITH RATCHET WHEEL, PUNCH UNIT FEED PAWL SHALL ENGAGE FIRST TOOTH BELOW HORIZONTAL CENTER LINE OF RATCHET FEED WHEEL WITH NO PERCEPTIBLE CLEARANCE."

TO ADJUST

REFINE FEED PAWL (PRELIMINARY) AND DRIVE LINK (PRELIMINARY) ADJUSTMENTS.

28 SINGLE-MAGNET


P34.651

TYPING REPER-

Page 69

FORATOR

2.62 Backspace Mechanism (Power Drive)



REQUIREMENT

BACKSPACE MECHANISM IN UNOPERATED POSITION. HIGH PART OF ECCENTRIC TO LEFT. ARMATURE AGAINST POLE FACE. LATCH RESTING ON ECCENTRIC ARM NOTCH. CLEARANCE BETWEEN ARMATURE BAIL EXTENSION AND LATCH EXTENSION

MIN. 0.005 INCH --- MAX. 0.020 INCH


TO ADJUST

SWING MAGNET CLOCKWISE OR COUNTERCLOCKWISE, AS NECESSARY, WITH MOUNTING SCREWS FRICTION TIGHT.

NOTE

THIS ADJUSTMENT IS MADE AT FACTORY AND SHALL NOT BE DISTURBED UNLESS A REASSEMBLY OF UNIT IS UNDERTAKEN. IF NECESSARY TO MAKE THIS ADJUSTMENT, PUNCH UNIT SHALL BE REMOVED. SEE DISASSEMBLY AND REASSEMBLY. REMAKE PUNCH UNIT POSITION ADJUSTMENT.

Backspace Mechanism (Power Drive) 2.63



REQUIREMENT

BACKSPACE MECHANISM IN UNOPERATED POSITION. ARMATURE OFF POLE FACE (DE-ENERGIZED). LATCH EXTENSION AGAINST END OF ARMATURE BAIL EXTENSION. ECCENTRIC ARM AT ITS CLOSEST POINT TO UNDERSIDE OF LATCH. CLEARANCE BETWEEN LATCH AND ECCENTRIC ARM

MIN. 0.005 INCH MAX. 0.025 INCH

TO ADJUST

POSITION LATCH WITH LATCH EXTENSION SCREW LOOSENED.

28 SINGLE-MAGNET


P34.651

TYPING REPER-

Page 71

FORATOR

2.64 Backspace Mechanism (Power Drive)



BACKSPACE MECHANISM IN UNOPERATED POSITION. CLEAR-ANCE BETWEEN TOP SURFACE OF NON-REPEAT ARM AND LOWEST POINT OF LATCH EXTENSION


MIN. 0.002 INCH

MAX. 0.010 INCH

TO ADJUST

POSITION ADJUSTING ARM WITH ARM SCREW LOOSENED FRICTION TIGHT.

2.65 Backspace Mechanisms (Manual and Power Drive)




28 SINGLE-MAGNET
TYPING
Page 73


Page 73


TYPING
REPERFORATOR

2.66 Automatic Noninterfering LTRS Tape Feed-out Mechanism



Remote-control Noninterfering LTRS Tape Feed-out 2.67 Mechanism






28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 75


2.68 Remote-control Noninterfering LTRS Tape Feed-out Mechanism




2.69 Remote-control Noninterfering LTRS Tape Feed-out Mechanism



2.70 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms



2.71 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms



28 SINGLE-MAGNET

P34.651

TYPING REPER-FORATOR

Page 79

LENGTH.

2.72 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms


(A) RELEASE ARM TO CHECK PLACE UNIT IN FEED-OUT CYCLE BY POSITIONING RELEASE LEVER ON LOWER STEP OF LATCH LEVER. AD-VANCE RATCHETS BEYOND TIME DELAY (HIGH PART OF TIME DELAY CAM BE-YOND TIME DELAY LEVER). POSITION FEED-OUT CAM AS SHOWN. ECCENTRIC REQUIREMENT **SCREW** MIN. 0.010 INCH--- MAX. 0.025 INCH (CLAMP NUT BETWEEN DRIVE ARM AND RELEASE ON OTHER END) ARM. TO ADJUST WITH CLAMP NUT LOOSENED, POSITION RELEASE ARM BY MEANS OF ECCENTRIC SCREW ON TIME DELAY LEVER. RELEASE ARM RELEASE LATCH LEVER LEVER LOWER STEP DRIVE ARM OF LATCH LEVER TIME DELAY LEVER FEED-OUT CAM TIME DELAY CAM DRIVE RELEASE ARM ARM RELEASE ARM SPRING (B) RELEASE ARM SPRING REQUIREMENT WITH CLUTCHES DISENGAGED AND DRIVE ARM LATCHED BY RELEASE ARM MIN. 2 OZS. --- MAX. 5 OZS. TO PULL SPRING TO INSTALLED

2.73 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms

(A) DRIVE ARM SPRING

PLACE UNIT IN FEED-OUT CYCLE BY POSITIONING RELEASE LEVER ON LOWER STEP OF LATCH LEVER AND ADVANCING HIGH PART OF TIME DELAY CAM BEYOND TIME DELAY LEVER.

ROTATE MAIN SHAFT UNTIL DRIVE ARM ROLLER IS ON LOW PART OF



(8)

DRIVE ARM ADJUSTING PLATE

TO CHECK

SET UP BLANK CODE COMBINATION (----)
IN SELECTOR. PLACE UNIT IN FEED-OUT
CYCLE BY POSITIONING RELEASE LEVER ON
LOWER STEP OF LATCH LEVER AND ADVANCING
HIGH PART OF TIME DELAY CAM BEYOND TIME
DELAY LEVER.ROTATE MAIN SHAFT UNTIL DRIVE
ARM ROLLER IS ON LOW PART OF FEED-OUT CAM.
MAKE SURE THAT RESET BAIL IS IN LOWER
POSITION.

REQUIREMENT

TO ADJUST

WITH CLAMP SCREW LOOSENED, POSITION DRIVE ARM ADJUSTING PLATE BY MEANS OF PRY POINT.


28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 81

2.74 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms



2.75 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms




TO ADJUST
WITH CLAMP SCREW LOOSENED, POSITION
RESET BAIL TRIP LEVER BY MEANS OF ADJUSTING SLOT.

28 SINGLE-MAGNET
TYPING

P34.651 Page 83

REPER-FORATOR

2.76 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms




WHEN OPERATING UNDER POWER, UNIT SHALL FEED OUT CORRECT LENGTH OF TAPE.

TO ADJUST

WITH SPRING POST LOOSENED, POSITION ADJUSTING PLATE.

2.77 Automatic and Remote-control Noninterfering LTRS Tape Feed-out Mechanisms

1



28 SINGLE-MAGNET
TYPING
P34.651 REPERPage 85 FORATOR

2.78 External Manual Interfering LTRS Tape Feed-out Mechanism

(A) Feed-out Lever

Requirement: Feed-out lever shall not touch sides of tape guide.

To Adjust: Bend feed-out lever.

Note: Remake manually operated triplever and triplever spring adjustments.


(B) Arm


Requirement: With cover positioned as specified in section containing the requirements and adjustments for typing reperforator cover, and arm just touching feed-out lever, handle shall be approximately horizontal. Gauge by eye.

To Adjust: Remove cover, loosen arm adjusting nut friction tight, position arm, and tighten nut.

2.79 Code-reading Contact Mechanisms (Make-only and Transfer Types)

UNLESS SPECIFICALLY STATED OTHERWISE, THE FOLLOWING CODE-READING CONTACT ADJUSTMENTS APPLY TO BOTH THE TRANSFER (BREAK BEFORE MAKE) TYPE AND MAKE-TYPE CONTACTS. WHEN AN ADJUSTMENT IS APPLICABLE TO BOTH TYPES, THE TRANSFER-TYPE CONTACTS ARE USED IN THE ILLUSTRATIONS. WHEN TESTING THESE CONTACTS ON ASR SETS, THE CONTROL KNOB SHALL BE IN THE K-T POSITION:






28 SINGLE-MAGNET

P34.651


TYPING REPER-

Page 87

2.80 Code-reading Contact Mechanisms (Make-only and Transfer Types)




NOTE:
SPACING CONTACTS (ON TRANSFER-TYPE CONTACT ASSEMBLIES ONLY)
ARE NORMALLY OPEN WHEN CONTACT ASSEMBLY IS REMOVED FROM UNIT.



NOTE:
TO INCREASE TENSION OF SPRING, IT MAY BE NECESSARY TO BEND BACKSTOP
AWAY FROM SPRING, BEND SPRING, AND THEN RE-BEND BACKSTOP TO MEET
REQUIREMENT OF SPACING CONTACT BACKSTOPS ADJUSTMENT ABOVE.

2.81 Code-reading Contact Mechanisms (Make-only and Transfer Types)




28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 89

2.82 Code-reading Contact Mechanism (Transfer Type)



WITH THE SELECTOR AND FUNCTION CLUTCHES DISENGAGED AND LATCHED, MANUALLY SELECT THE LTRS CODE COMBINATIONS AND TRIP THE FUNCTION CLUTCH.

CLEARANCE BETWEEN PUNCH SLIDE INSULATOR

AND SWINGER CONTACT SPRING


MIN. 0.028 INCH


TO ADJUST

POSITION CONTACT BRACKET WITH ITS MOUNTING SCREWS LOOSENED TO MEET REQUIREMENT (1). TO PRY BRACKET TO LEFT, INSERT SCREWDRIVER BETWEEN BRACKET AND LEFT EDGE OF MOUNTING SCREWS; TO PRY BRACKET TO RIGHT, INSERT SCREWDRIVER BETWEEN BRACKET AND RIGHT EDGE OF MOUNTING SCREWS. CHECK REQUIREMENT (2). IF NOT MET, REFINE ADJUSTMENT.

Code-reading Contact Mechanism (Make-only Type) 2.83

CONTACT BRACKET (APPLIES TO MAKE-TYPE CONTACTS ONLY) --- PRELIMINARY





TO ADJUST POSITION CONTACT BRACKET WITH MOUNTING SCREWS FRICTION TIGHT. TO PRY BRACKET TO LEFT,
INSERT SCREWDRIVER BETWEEN BRACKET AND
LEFT EDGE OF MOUNTING SCREW; TO PRY BRACKET TO RIGHT, INSERT SCREWORIVER BETWEEN BRACKET AND RIGHT EDGE OF MOUNTING SCREW.

28 SINGLE-MAGNET

P34.651


TYPING REPER-FORATOR

Page 91

2.84 Auxiliary Timing Contact Mechanisms (Single-contact and Double-contact Types)

NOTE:
THERE ARE TWO TYPES OF TIMING CONTACT ASSEMBLIES, SINGLE AND DOUBLE.
SINGLE-CONTACT ASSEMBLIES HAVE A FRONT CONTACT ONLY, NO REAR CONTACT.
IF UNIT IS EQUIPPED WITH A DOUBLE-CONTACT ASSEMBLY, THE FOLLOWING
ADJUSTMENTS APPLY TO BOTH FRONT AND REAR CONTACTS.


NOTE:
IN CASE OF SINGLE-CONTACT ASSEMBLY,
MAKE CERTAIN CONTACT BRACKET MOUNTING
SCREWS ARE CENTRALLY LOCATED IN ELONGATED
SLOTS, AND PROCEED TO NEXT ADJUSTMENT.



MOUNTING SCREWS LOOSENED.

2.85 Auxiliary Timing Contact Mechanisms (Single-contact and Double-contact Types)

IT IS RECOMMENDED THAT THE FOLLOWING TIMING CONTACT ADJUSTMENTS
BE MADE WITH CONTACT ASSEMBLIES REMOVED FROM THE UNIT.




28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 93

2.86 Auxiliary Timing Contact Mechanisms (Single-contact and Double-contact Types)



MAX. 0. 055 INCH


TO ADJUST

POSITION CONTACT BRACKET WITH MOUNTING SCREWS LOOSENED.

NOTE:

ON UNITS EQUIPPED WITH DOUBLE-CONTACT AS-SEMBLIES , RECHECK CONTACT BACKSTOP ADJUST-MENT. IF REQUIREMENT IS NOT MET, REFINE CONTACT BRACKET ADJUSTMENT.

2.87 LTRS-FIGS Contact Mechanism



28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 95 FORATOR

2.88 Contact-timing Measurements (To Zero Test Set)


THE FOLLOWING TESTS REQUIRE THE USE OF A 28A STROBOSCOPIC TEST SET OR A 1A TELE-TYPEWRITER TEST SET. THEY SHALL BE MADE AFTER THE CONTACT ASSEMBLIES HAVE BEEN ADJUSTED AS INSTRUCTED ON THE PRECEDING PAGES. WHERE REQUIREMENTS ARE NOT MET, DESIGNATED ADJUSTMENTS MUST BE REFINED. AND/OR RELATED LENGTHS MAY HAVE TO BE CHANGED TO MEET TIMING REQUIREMENTS.

TESTS ON 600 OPERATION-PER MINUTE UNITS OR LOWER SHALL BE MADE WITH THE REPER-FORATOR AND THE TEST SET OPERATING AT 600 O.P.M. TESTS OF UNITS USED ON THE AUTOMATIC SEND-RECEIVE (ASR) SET SHALL BE MADE WITH THE CONTROL KNOB OF THE 28ASR IN THE K-T POSITION AND WITH THE UNIT AND THE TEST SET OPERATING AT 600 O.P.M.

OBSERVATIONS ARE TO BE MADE OF A NEON TRACE ON THE GRADUATED DISK OF A TEST SET.

TRACE WILL HAVE TENDENCY TO "JUMP", THAT IS, IT WILL NOT BE STEADY ENOUGH TO BE
ACCURATELY MEASURED. VARIATION MAY BE AS HIGH AS TEN DIVISIONS ON SCALE. MINIMUM
SIGNAL LENGTH IS MEASURED BETWEEN LATEST START AND EARLIEST END OF ALL TRACES.

MAXIMUM SIGNAL LENGTH IS MEASURED BETWEEN EARLIEST START AND LATEST END OF ALL TRACES.




TO ZERO TEST SET

"CONNECT NEON TRACE TO NO. 1 CODE-READING CONTACT (REARMOST). WITH UNIT RECEIVING LTRS CODE COMBINATIONS, OBSERVE AND NOTE POINT AT WHICH TRACE ENDS. TRACES WILL JUMP AS DESCRIBED ABOVE; NOTE EARLIEST END OF TRACES. REPEAT FOR REMAINING CONTACTS. OF ALL TRACES OBSERVED, CHOOSE ONE THAT STARTS THE LATEST. SET "START-ZERO" MARK OF SCALE AT LATEST START OF CHOSEN TRACE. RECORD EARLIEST END OF CHOSEN TRACE FOR FUTURE ADJUSTMENT REFERENCES.

2.89 Contact-timing Measurements for Code-reading Contacts

NOTE: TEST PROCEDURES ON THIS PAGE APPLY TO 600 O.P.M. UNITS OR LOWER ONLY.



CODE-READING CONTACTS

(1) ZERO TEST SET AS INSTRUCTED.

(2) CONNECT NEON TRACE TO MARKING SIDE OF A CODE-READING CONTACT (NORMALLY OPEN WHEN UNIT IS IN IDLE CONDITION). WITH UNIT RECEIVING CONTINUOUS LTRS CODE COMBINATIONS, OBSERVE TRACE.

REQUIREMENTS

A. SIGNAL LENGTH MIN. 450 DIVISIONS MAX. 594 DIVISIONS

B. BOUNCE SHALL END WITHIN MAX. OF 20 DIVISIONS OF EARLIEST START AND LATEST, END OF ALL TRACES.

(3) (APPLIES TO TRANSFER-TYPE CONTACTS ONLY) CONNECT NEON TRACE TO BOTH SIDES OF CONTACT. WITH UNIT RECEIVING LTRS CODE COMBINATIONS, OBSERVE TRACE. REQUIREMENTS

A. BREAK IN TRACE INDICATING BREAK BEFORE MAKE

MIN. 10 DIVISIONS

B. SIGNAL LENGTH OF SPACING SIDE OF CONTACT

MIN. 100 DIVISIONS

C. BOUNCE SHALL END WITHIN 30 DIVISIONS OF EARLIEST START AND LATEST END OF TRACE.

(4) TO ADJUST

A. IF REQUIREMENTS UNDER (2) A., (3) A., OR (3) B. ARE NOT MET, REFINE CONTACT BRACKET ADJUSTMENT. WHEN REFINING (2) A., ATTEMPT TO ADJUST TOWARD MAXIMUM SIGNAL LENGTH.

B. IF BOUNCE REQUIREMENTS UNDER (2) B. AND (3) C. ARE NOT MET, REFINE SWINGER CONTACT SPRING AND SPACING CONTACT SPRING TENSIONS.

C. IF ANY REFINEMENTS ARE NECESSARY, REPEAT COMPLETE TEST PROCEDURE.

28 SINGLE-MAGNET


P34.651

TYPING REPER-

Page 97

2.90 Contact-timing Measurements for Auxiliary Timing Contacts

TEST PROCEDURES ON THIS PAGE APPLY ONLY TO 600 O.P.M. UNITS (BELL 8281 SYSTEM) USING ONE-CYCLE CAMS.



TIMING CONTACTS

- (1) ZERO TEST SET AS PREVIOUSLY DESCRIBED.
- (2) REAR CONTACT
 - A. CONNECT NEON TRACE TO RIGHT SIDE OF REAR CONTACT (NORMALLY OPEN WHEN UNIT IS IN IDLE CONDITION). WITH UNIT RECEIVING LTRS CODE COMBINATIONS, OBSERVE TRACE. REQUIREMENTS


 - EARLIEST START MIN. OF 35 DIVISIONS AFTER START-ZERO MARK.

 LATEST END MIN. OF 35 DIVISIONS BEFORE EARLIEST END OF CODE-READING CONTACT TRACES.
 - MIN. TRACE LENGTH 225 DIVISIONS.
 - BOUNCE SHALL END WITHIN MAX. 5 DIVISIONS OF START AND END OF ANY TRACE.
- (3) FRONT CONTACT
 - A. CONNECT NEON TRACE TO BOTH SIDES OF FRONT CONTACT. WITH UNIT RECEIVING LTRS CODE COMBINATIONS, OBSERVE TRACE. REQUIREMENTS
 - BREAK IN TRACE TO INDICATE BREAK BEFORE MAKE MIN. 10 DIVISIONS
 - 2. BETWEEN EARLIEST STARTS OF TRACES OF RIGHT AND LEFT (NORMALLY OPEN AND NORMALLY CLOSED) SIDES OF CONTACT MIN. 325 DIVISIONS --- MAX. 420 DIVISIONS
 - 3. BOUNCE SHALL' END WITHIN MAX. 5 DIVISIONS OF EARLIEST START AND LATEST END OF ANY TRACE.
- (4) TO ADJUST
 - A. IF TIMING REQUIREMENTS UNDER (2) A. 1., 2., 3., AND (3) A. 1. AND 2. ARE NOT MET, REFINE CONTACT BRACKET ADJUSTMENT AND/OR RIGHT CONTACT GAP, LEFT CONTACT GAP, SWINGER CONTACT SPRING, AND LEFT CONTACT SPRING ADJUSTMENTS.

 B. IF BOUNCE REQUIREMENTS UNDER (2) A. 4. AND (3) A. 3. ARE NOT MET, REFINE SWINGER CONTACT SPRING AND LEFT CONTACT SPRING TENSIONS.

 - IF ANY REFINEMENTS ARE NECESSARY, REPEAT COMPLETE TEST PROCEDURE.

2.91 Contact-timing Measurements for LTRS-FIGS Contacts



IF UNIT IS EQUIPPED WITH CODE-READING AND/OR TIMING CONTACTS, TEST IS TO BE MADE AFTER INSTALLATION AND ADJUSTMENT OF THESE CONTACTS

LTRS-FIGS CONTACTS

TO CHECK
CONNECT CABLE LEADS OF LTRS-FIGS CONTACT TO NEON TRACE
LAMP OF TEST SET. SET CONTROL SWITCHES OF TEST
SET TO FOLLOWING POSITIONS: (1) VIEW-TRANSMIT SWITCH TO VIEW;
(2) LINE-DIST. SWITCH TO LINE; AND MOTOR SWITCH TO ON. ALTERNATELY SELECT LTRS (12345) AND FIGS (12-45). SET START-ZERO
MARK OF TEST-SET SCALE AT START OF CONTACT TRACE. CONNECT
RIGHT SIDE OF FRONT TIMING CONTACT (PROBE) TO NEON TRACE
LAMP; RECORD START AND END OF TRACE. RECONNECT LTRS-FIGS
CONTACT TO TRACE LAMP AND ALTERNATELY SELECT LTRS-FIGS.

REQUIREMENT

(1) NO CHATTER OR BOUNCE OF LTRS-FIGS CONTACT DURING
TIME WHEN TIMING CONTACT IS CLOSED.

(2) TRACE OF LTRS-FIGS CONTACT START MIN. OF 40 DIVISIONS BEFORE START OF TRACE OF TIMING CONTACT AND END MIN. OF 5 DIVISIONS AFTER END OF TIMING CONTACT.

TO ADJUST

(1) IF (1) OF REQUIREMENT IS NOT MET, REFINE MIDDLE AND LOWER CONTACT SPRING ADJUSTMENTS

(2) IF (2) OF REQUIREMENT IS NOT MET, REFINE MOUNTING BRACKET ADJUSTMENT,

28 SINGLE-MAGNET

P34.651

TYPING REPER-

Page 99

3. ASSOCIATED BELL SYSTEM PRACTICE

3.01 The following Bell System Practice provides additional information that may be required in connection with this section.

Subject		Section
Alphabetical Index of 28-type Equipment,	Bell	16.4 -1.0 .1111-1.0.011
System Practices, and Associated 28 ASR tion Drawings		P34.001

CHANGES AUTHORIZED BY P98 SERIES BELL SYSTEM PRACTICES

Par. No.		Changes as Authorized by Section
2.15 (B)	Punch Slide Downstop Position	P98.871
2.27 (B)	Pushbar Operating Blade (Final)	P98.874
2.32 (A)	LTRS-FIGS Yield Arms	. P98.873
2.39 (A)	Axial Output Rack Guide Roller	P98.903
2.42	Rotary Correcting Lever	. P98.874
2.45 (A)	Typewheel	. P98.894
2.47 (B)	Ribbon-feed Eccentric Stud	. P98.873
2.80 (B)	Spacing Contact Backstops	. P98.748